

論文 / 著書情報
Article / Book Information

題目(和文)	
Title(English)	Study of two-plane couplers having arbitrary power ratio and their applications to two-dimensional beam switching matrices
著者(和文)	LI Qi
Author(English)	Qi Li
出典(和文)	学位:博士(学術), 学位授与機関:東京工業大学, 報告番号:甲第12586号, 授与年月日:2023年9月22日, 学位の種別:課程博士, 審査員:廣川 二郎,阪口 啓,西方 敦博,青柳 貴洋,TRAN GIA KHANH,高橋 徹
Citation(English)	Degree:Doctor (Academic), Conferring organization: Tokyo Institute of Technology, Report number:甲第12586号, Conferred date:2023/9/22, Degree Type:Course doctor, Examiner:,,,,,
学位種別(和文)	博士論文
Category(English)	Doctoral Thesis
種別(和文)	論文要旨
Type(English)	Summary

論文要旨

THESIS SUMMARY

系・コース： Department of, Graduate major in	電気電子 電気電子	系 コース	申請学位（専攻分野）： Academic Degree Requested	博士 Doctor of	(Philosophy)
学生氏名： Student's Name	Qi LI		指導教員（主）： Academic Supervisor(main)	廣川 二郎	
			指導教員（副）： Academic Supervisor(sub)		

要旨（英文 800 語程度）

Thesis Summary (approx.800 English Words)

Beam-switching matrix to realize multi-beams with spatial orthogonality has attracted a great deal of attention due to its vast potential application on satellite communication, as well as 5G/6G terrestrial or non-terrestrial communication. Among various transmission line technologies available for millimeter-wave frequencies, the waveguide stands out by showing its inherent superiority with low loss. This doctoral dissertation accomplishes the theoretical analysis of the two-plane coupler having arbitrary coupling ratio in the H-plane and E-plane directions, and its application to two-dimensional beam switching matrices for the purpose of functionality enhancement and miniaturization. Chapter 1 gives a brief introduction concerning the background, application and development of beam forming networks, including beam-switching matrices and lens-based antennas. The motivation of this dissertation comes up, which focuses on the exploration of the two-plane coupler realizing arbitrary coupling ratios and two-dimensional beam-switching matrices with the beam number other than a power of two and with a different number of beams in two orthogonal directions. Chapter 2 presents a theoretical analysis of the two-plane coupler having arbitrary coupling ratios in the H-plane and E-plane directions. Based on two-dimensional even-odd method analysis, it is revealed that the essence to control coupling ratio of the two-plane coupler is to adjust comparative transmission phases among four types of the quarter models assigning electrical and magnetic walls on the two-dimensional symmetrical planes properly . In addition to usual coupling mechanism with equivalence to cascading of the H-plane and E-plane couplers, other two coupling mechanisms are also be introduced. Subsequently with the above-mentioned theory part, based on a hybrid of finite element method and mode matching method, a prototype of the two-plane coupler having $1:\sqrt{2}$ in the H-plane direction and $\sqrt{2}:1$ in the E-plane direction working from 27.0GHz to 29.5GHz, with an 8.85% fractional bandwidth, is designed and fabricated to verify the theoretical analysis. For both the simulated and measured results across the considered bandwidth, the reflections are all suppressed under -15dB, the deviation of the output amplitude is in no excess of 2dB and the phase digressions are less than 20°. In addition, the designing sample of a H-plane coupler and an E-plane coupler is provided, cascading of which can be equivalent to the two-
--

plane coupler. Comparing to the cascade of the one-plane couplers, the two-plane coupler gives downsize rates as 58.4% and 50.1% with regard to length and volume, respectively.

Chapter 3 introduces an two-dimensional one-body 3×3 -way hollow-waveguide Nolen matrix using a two-plane unequal division coupler working from 27.65GHz to 28.85GHz, corresponding to a 4.1% fractional bandwidth. The variation of the transmission of the proposed two-plane unequal division coupler is within ± 0.5 dB in amplitude and $\pm 10^\circ$ in phase over the considered frequency band. For the designed two-dimensional 3×3 -way Nolen matrix, a 2.5 dB output port power imbalance and a 0.86 dB insertion loss in maximum are observed in simulation across the analyzed bandwidth. Far field measurements are implemented to verify the radiation performance and to evaluate the realized gain with a reference to a standard horn antenna. The maximum realized gain of the two-dimensional 3×3 -way Nolen matrix at 28.25GHz is reached at boresight with a value of 15.5 dBi in measurement and 15.7 dBi in simulation. The minimum realized gain in measurement is obtained for a two-dimensionally tilted beam with a value of 12.0 dBi, while in simulation of 12.9 dBi. It is the first time that a two-dimensional one-body hollow-waveguide Nolen matrix with the port number other than a power of two is reported, also including the first application of a two-plane coupler having unequal output division to beam-switching matrix network. The future bandwidth enhancement could be explored by adopting more advanced manufacturing technologies, such as 3-D printing.

Chapter 4 introduces a two-dimensional hollow-waveguide 6×4 -way beam switching matrix working from 27.25GHz to 29.25GHz, with a 7.1% fractional bandwidth. This is the first time that a two-dimensional waveguide beam-switching matrix is proposed with different number of beams in two orthogonal directions. Taking advantage of the two-dimensional symmetry in the transverse directions, the design complexity is reduced. The two-dimensional 6×4 -way matrix has a 2.2 dB insertion loss over the operation bandwidth. The radiation performance is verified by planar scanning near-field measurements. The maximum directivity is obtained with a value of 21.3 dBi in measurement and 21.1 dBi in simulation. The minimum directivity in measurement is 17.7 dBi, with a tilted angle of 34° with reference to boresight, corresponding to a scan loss of 3.4 dB, while that in simulation is 18.0 dBi, with an tilted angle of 35° with reference to the boresight, counterpart to 3.1 dB scan loss.

Chapter 5 gives the overall summary to complete the dissertation, with some perspective views on potential future works, such as to enhance for the bandwidth of the two-plane coupler by introducing asymmetry in the longitudinal direction, and to accomplish the theoretical framework of one-dimensional generalized 2N-way matrix with symmetrical configuration.

備考：論文要旨は、和文 2000 字と英文 300 語を 1 部ずつ提出するか、もしくは英文 800 語を 1 部提出してください。

Note: Thesis Summary should be submitted in either a copy of 2000 Japanese Characters and 300 Words (English) or 1copy of 800 Words (English).

注意：論文要旨は、東工大リサーチリポジトリ(T2R2)にてインターネット公表されますので、公表可能な範囲の内容で作成してください。

Attention: Thesis Summary will be published on Tokyo Tech Research Repository Website (T2R2).